

GA6HRS

6 kW, 120/240V, Honda, Electric Start

When your job demands a power source that is versatile enough to handle changing requirements, Multiquip's portable 6kW models are the number one choice.

- Brushless generator design requiring less maintenance
- 100% copper windings for maximum conductivity
- Lightweight and compact design for easy transport
- Twin duplex receptacles and three T-Lock receptacles for job site versatility
- Heavy-duty 1-inch (25 mm) steel pipe frame and shock mounts protect the generator
- Wheel kit - Hour meter - Folding lifting bale are now standard equipment
- Powered by Honda's GX-340 engine with low-oil shutdown, idle control and electric start
- Full panel GFCI protection - OSHA and NEC compliant



Unit Specifications

Alternator Design	Brushless	
Frequency	60 hz	
Phase	Single Phase	
Voltage	120/240 V	
Sound level at 30 ft	75 dBA	
Fuel Tank Capacity	5 gal	19 L

Power Generation

	Maximum	Continuous
Watts	6000 W	5000 W
Amps at 120V	50 A	41.6 A
Amps at 240V	25 A	20.8 A

Receptacles & Circuit Breakers

Main Circuit Breaker	23 A	
Number of Poles	2	
1 Receptacle of Each:	L5-20R 125V T-Lock 20A L5-30R 125V T-Lock 30A L14-30R 125/250V T-Lock 30A	
2 Receptacle of Each:	5-20R 125V GFCI 20A	

Dimensions & Weights

Overall Length	27 in	69 mm
Overall Width	22.25 in	57 mm
Overall Height	24 in	61 mm
Operating Weight	259 lb	117 kg
Shipping Weight	218 lb	99 kg

Engine Specifications

Engine Make/Model	Honda GX-340	
Start Method	Recoil/Electric	
Engine Power	9.5 HP	7.1 kW
Engine RPM	3600	
Fuel Type	Gasoline	

Notice: Features and equipment specifications are subject to change without notice.